

ROCKBOARD®

by WARWICK

Installation Manual for RockBoard® MOD Rack

Mounting Rack for MOD V2s on non-RockBoard Pedalboards



English

Thank you for choosing a **RockBoard®** MOD Rack! The **RockBoard®** MOD Rack will hold your MOD All-in-One Patchbays on non-**RockBoard®** pedalboards in place. It offers several mounting orientations, depending on the design of your pedalboard.



Mounting

With many pedalboards using the popular horizontal bar design, common mounting options are pictured below:



Step 1

Select a mounting position and orientation for the MOD Rack on your pedalboard. To mount the MOD Rack, mark the position of the mounting holes using a pencil or pen. Depending on the size and construction of your board, certain mounting orientations might not be possible.



Step 2

Use a drilling machine with 2.5 mm metal drill and drill holes in your pedalboard at the marked positions.



Step 3

The included 10 mm long mounting screws are self-tapping. This means they will cut their own threads in the material of the drill hole. Because of this the first few turns will be difficult until the threads have been cut. Do not screw them in at an angle. Use the included TX10 screwdriver to screw the 10 mm long mounting screws in and cut the threads.



Step 4

Once the mounting screws become easier to turn, the threads have been cut properly. Remove the mounting screws. Now it's time to mount your MOD RACK onto your pedalboard. Depending on the mounting position, you may want to add the included counter nuts for additional security.



Step 5

Place your **RockBoard®** MOD All-in-One Patchbay in the MOD Rack and position it. Use the remaining four 3 mm long MOD mounting screws to lock the MOD in place. Depending on your mounting orientation you may have to detach the MOD's front plate (see manual).



Step 6

Connect the **RockBoard®** MOD All-in-One Patchbay to your setup. Your **RockBoard®** MOD Rack is now completely mounted.

Note: The manufacturer reserves the right to change these specifications without notice.

USA DISTRIBUTION: Framus & Warwick Music USA, Inc. | info@rockboard.net | 629.202.6790

CHINESE DISTRIBUTION: Warwick Music Equipment Trading (Shanghai) Co. Ltd. | info@warwick.cn | +8621 34060110

NORTH EUROPEAN DISTRIBUTION: www.rockboard.de | info@rockboard.de | www.w-distribution.de | www.facebook.com/warwickmusicdistribution

Headquarters: Warwick GmbH & Co. Music Equipment KG | 08258 Markneukirchen / Germany | +49 (0) 37422 / 555 - 0

Family Owned • Solar Powered • Sustainably Manufactured in a Green Environment